

QuickMount Dual Remote Mount Interface

Turn any Motorola Professional Series CDM 750, CDM 1250 or CDM 1550 Radio in to a dual mount installation with the QuickMount Interface. All the programmed functions are available from either controlhead including fully independent VOLUME and BACKLIGHTING control.

Each Quick Mount Interface comes with Power Cable and Speaker Pigtail. All Motorola parts including radio, controlheads, data cables and mounting hardware need to be purchased from an authorized Motorola dealer or service shop.



Specifications:

Input Voltage	13.2Vdc (10-16Vdc) (-)
Input Current Off	< 2mA
Input Current On/No Audio.....	< 300mA
Full Rated Audio	≈ 4.5A with input fuse rating of 5A
Rated Audio	3W @ 22 ohms per control head 13W @ 4 ohms per external speaker connector
Audio Distortion	< 4% typical
Operating Temperature.....	-30° to 60° C
Storage Temperature	-55° to 85° C
Dimensions.....	6-13/64" (D) x 5-3/8"(W) x 1-45/64"(H)
Weight.....	1 lb 8 oz

